USB-C COMPARISON CHART



In order to help users navigate their way around the different cables available today, we have created the '5-star' criteria system to rate and classify cables in line with the 5 most crucial operational aspects. On this page, you can find a short explanation of these criteria as well as what the corresponding star levels mean for each, and further on you can find our Comparison Chart including a wide range of cables and how they performed during our tests against these 5 criteria.

	P		ss-				
5 Criteria 5 Stars	4K 60FPS Video and Audio 4-Lane DisplayPort Alt mode	Mouse, Keyboard, Speakerphone, Thumb Drive and Webcam USB 2.0 480 Mbps "High Speed"	4K Webcam, SSD storage USB 3 Gen1 5 Gbps "SuperSpeed"	Fast Charging of Laptops, Tablets and Phones 60W / 3 A charging and eMarker	Convenient to use and to install Connector dimensions according to standard; No bulky repeaters along the cable		
*	 Up to 4K60 (4-Lane DP) 	 Stable with all host 	Stable with all hostsAll wires are present	 At least 60 W PD support AND Proper eMarker 	 Convenient to use and to install (No design flaws) 		
*	 Up to 4K30 (2-Lane DP) 	 Unstable with some hosts 	 Unstable with some hosts 	 PD supports less than 60W OR Missing eMarker 	 At least one design flaw 		
	No support	No supportMissing wires	No supportMissing wires	No PD supportNo eMarker	 Multiple design flaws 		

	ommended Cables aurus UCX Products	Most Important						Least Important		
-	-C to USB-C)	Length	Category	4K60 Video	USB 2.0	USB 3.X	Charging + eMarker	Conve- nience	Comments	Rating
	Lightware CAB-USBC-T100A	1m	Copper	*	*	*	*	*		****
	Sommer HI-U4CC-0100	1m	Copper	*	*	*	*	*		****
	Lightware CAB-USBC-T200C	2m	Copper	*	*	*	*	*		****
	Apple Thunderbolt 4 Pro	1,8m/3m	Active Copper	*	*	*	*	*		****
	Apple Thunderbolt 3 Pro	2m	Active Copper	*	*	*	*	*		****
	TrippLite U420-006-5A	1,8 m	Copper	*	*	*	*	*	Rigid cable	****
	Lightware CAB-USBC-T200A/T300A	2m/3m	Copper	*	*	*	*	*	Only 60W charging power supported	****
Recommended for Taurus UCX	Lightware CAB-USBC-T400B/500B	4m/5m	Copper (Microcoax)	*	*	*	*	*	Only 60W charging power supported	****
r Tau	Atlona AT-LC-UC2UC-2M	2m	Copper	*	*	*	*	*	Only 60W charging power supported	*****
ed for	Freeport 26-715-06 (Extron)	1,8m	Copper	*	*	*	*	*	Only 60W charging power supported	*****
nend	Delock 83668	2m	Copper	*	*	*	*	1	Only 60W charging power supported; Rigid cable	****
Recomn	Vivolink PROUSBCMM3	3m	Copper	*	*	*	*	*	Only 60W charging power supported	*****
	CableWholesale 10U4-32006	1,8m	Copper	*	*	*	☆	*	Only 30W charging power supported	****
	Comprehensive USB3-CC-10SP	3m	Copper	*	*	*	☆	*	Only 15W charging power supported	****
	CableWholesale 10U4-32010	3m	Copper	*	*	*	☆	*	Only 30W charging power supported	****
	FSR LP-TBRT-5-USBC-USBC	5m	Copper	*	*	*	☆	*	Only 30W charging power supported	****
	Kramer CA-U32/FF-10	3m	Copper	*	*	*	*		Only 60W charging power supported; Rigid cable	****
	Lightware CAB-USBC-AOC800K/AOC1000K	8m/10m	Active Optical			*	*	*	Only 4K30 video (2-lane DP Alt mode) supported; 2 Tier added at the USB2.0 topology; Active optical cable with specific direction;	****
	TTL-Taiwan 20105	2m	Copper	*	*	*	☆	1	eMarker chip cannot be read; bigger cable head	****

Recommended Cables for Taurus UCX Products(USB-C to USB-C)Length			Most Important						Least Important	
		Length	Category	4K60 Video	USB 2.0	USB 3.X	Charging + eMarker	Conve- nience	Comments	Rating
	Vivolink PROUSBCMM4	4m	Copper	*	*	*	*	*	USB2.0 lines does not work with some tested laptops*; only 60W charging power supported	****
	Bizlink KSC001R-16X	4m	Active Copper	1	*	*	*	*	Only 4K30 video (2-lane DP Alt mode) supported; only 60W charging power supported; Active copper cable with specific direction;	
	Extron USBC Pro/30	9,1m	Active Optical	*	*	*	*		Only 4K30 video (2-lane DP Alt mode) supported; 2 Tier added at the USB2.0 topology, not recommended for complex USB systems	
	Tether Tools CUC15	4,6m	Copper	*	*	*	☆	*	USB2.0 and USB3 lines does not work with some tested laptops*; only 30W charging power supported	***
At your own risk	Vivolink PROUSBCMM5	5m	Copper	*	*	*	☆	*	USB2.0 and USB3 lines does not work with some tested laptops*; only 30W charging power supported	***
	M-CAB 2200046	3m	Copper	*	*	*	☆		USB2.0 and USB3 lines does not work with some tested laptops*; Missing E-marker	***
	Freeport KFCB201208	4,5m	Copper	*	*	*	☆	1	USB2.0 and USB3 lines does not work with some tested laptops*; only 30W charging power supported	***
	Newnex U4SLC01C01-050	5m	Copper	*	*	*	☆	1	USB2.0 and USB3 lines does not work with some tested laptops*; Missing E-marker	***
	Kramer CLS-AOCU32/FF-35	10,7m	Active Optical	*		*	☆	*	Only 4K30 video (2-lane DP Alt mode) supported; USB2.0 lines does not work with some tested laptops*; only 30W charging power supported;	
	Purelink FX-I600-010	10m	Active Optical			*	☆	*	Only 4K30 video (2-lane DP Alt mode) supported; 2 Tier added at the USB2.0 topology, not recommended for complex USB systems; only 30W charging power supported	***
	Cosemi 175USH31CCMM015M001	15m	Active Optical	*	*	☆	☆	☆	DP Alt mode only (no USB3 data); only 30W charging power supported	**

*Tested hosts: Lenovo ThinkPad X280 Laptop; Dell G5 5587 Laptop. **These results were** experienced with Lightware Taurus UCX product, your experience may vary.

Recommended Cables for Taurus UCX Products (USB-C to USB-C)			Most Important				Least Important			
		Length	Category	4K60 Video	USB 2.0	USB 3.X	Charging + eMarker	Conve- nience	Comments	Rating
NCX	iiglo II-USBAMUSBC30-B300	3m	Copper	*	*		☆	*	USB3 lines does not work with some tested laptops*; only 30W charging power supported; Failed Total phase "Eye pattern" instrument test	****
n sn	Club3D CAC-1535	5 m	Active Copper	*	☆	☆	*	1	4 Iane DP Alt mode only (no USB3 and no USB2.0 data)	**
ır Taurus	HP 9JH45AA	5 m	Active Copper	*		☆	☆	1	4 Iane DP Alt mode only (no USB3 data); USB2.0 lines does not work with some tested laptops*; only 15W charging power supported	**
ded fo	Cable Matters 201034-BLK-5m	5 m	Active Copper	*	*		☆	☆	USB2.0 and USB3 lines does not work with some tested laptops*; only 30W charging power supported; Amplifier in the middle	**
Not recommended for	Newnex ULK10G-CC-8M	8 m	Active Copper	*			☆	☆	USB2.0 and USB3 lines does not work with some tested laptops*; only 30W charging power supported; Repeater in the middle, and quite rigid	
	SmartAVLink SCVC-3100-20	20 m	Active Optical	*	☆	☆	☆	☆	4 lane DP Alt mode only (no USB3 and no USB2.0 data); No charging power	*
	Club3D CAC-1589	20 m	Active Optical	*	☆	☆	☆	☆	4 Iane DP Alt mode only (no USB3 and no USB2.0 data); No charging power	*
No Video with Taurus UCX	SmartAVLink KUCC-3100-020	2 m	Copper	☆	*	*	☆	*	No Video and Audio due to missing SuperSpeed wires; only 30W charging power supported	***
	Apple USB-C charge cable	1 m / 2m	Copper	☆	*	☆	*	*	No Video and Audio due to missing SuperSpeed wires; For charging only	***
	Belkin Thunderbolt 3	2m	Active Copper		*	☆	*	*	No DP Alt mode and no USB3 data supported, therefore video and audio signals won't be transmitted for Taurus UCX;	***
	Lanberg CA-CMCM-31CU-0030-BK	3m	Copper			*	☆	*	No USB3 lines for video; only 15W charging power supported; USB2.0 lines does not work with some tested laptops*	**

Cables that don't support video transmission are **not** 'host cables' by Lightware's definition!

*Tested hosts: Lenovo ThinkPad X280 Laptop; Dell G5 5587 Laptop. **These results were experienced with Lightware Taurus UCX product, your experience may vary.**